

HMMA-120 PLAY

120W Mini Digital Mixer-Amplifier with USB/FM/BT

HMMA PLAY series is designed for all those PA applications where space is quite zero.

In half 19" Rack Unit there is a Class-D amplifier with powers ranging from 35W to 120W (70-100V or 4-16ohm outputs), a USB/BT/FM Radio with Remote Control, and a mixer for the control of the individual audio sources and the master.

It is also possible to connect these amplifiers to your alarm system and power a 24V in the event of a fire prevention system. Really the perfect solution for small business premises.



PRODUCT DETAILS

Key features

Compact design, Half 19" Rack Unit Size

100V-70V & 4-16 ohm Speaker Output

120 Rated Power

Built-in USB Player, FM Radio & BT Streaming with remote controller

2 MIC inputs (MIC1 with 6.3mm Jack; MIC2 with 2 XLR and Phantom)

1 EMC input, 2 Line Inputs, 1 Line Output

High-Performance Class-D amplifier with Switching Power Supply

Individual Volume control for Mic 1-2, Line 1-2, MP3/FM/BT

Bass/Treble and Master Volume Control

DC24V Auxiliary Power Input

Specifications

Rated Power	120W @4ohm
Speaker Outputs	100V or 70V & 4Ohms-8 Ohms-16 Ohms
Connectors	Mic1 Input with unbalanced 6.3mm Jack; MIC2 with balanced XLR and Phantom Power; Line1-2 Inputs and Line Output with RCA
Knob Controls	Microphone 1-2, Line1-2, MP3/FM, bass/treble and master
Sensitivity	MIC 1&2 5mV; AUX 1&2 350mV; EMC 350mV
MIC frequency response	180Hz-10kHz (± 3 dB)
AUX frequency response	70Hz-16kHz (± 3 dB)
Noise	<5mV (4 ohm load output terminal)
THD	<1% 1KHz
Protection	Short-Circuit, Clip, Overload and High-Temp Protection
Bass-Treble Adjustment	10dB (± 2)
USB Connection	Type-B, Female
USB Drive Format	FAT32 format -32GB Max
Player File Formats	MP3 e streaming audio wireless BT
BT Receiving Distance	10m
BT Standard	BT2.1+EDR
Power Requirement	AC~110-220V
Priority	EMC > MIC1 > Others
Unit Size (W×D×H)	247×198×66 mm
Packing size (W×D×H)	343×302×121 mm
Net Weight	3.0kg
Gross Weight	3.7Kg